

**USE:** Determine the application of transformer rated meter sockets supplied by the Company


PREVIOUS REVISION	ORIGINATED	PREVIOUS NUMBER
04-01-99	04-99	

**LATEST REVISION:** Added single phase, three wire, 240/480 volt to standard.

**REFERENCE:** M 63-400, latest revision

**SPECIFICATION:**

**1. TYPE TR-5 (5 jaws)**




1.1 Application

- 1.1.1 Single phase, two wire, 120 or 240 volt, over 400 amp
- 1.1.2 Single phase, two wire, primary voltage service

1.2 Stores Item Number - **236733**

**2. TYPE TR-6 (6 jaws)**




2.1 Application

- 2.1.1 Single phase, three wire, 120/240 volt, over 400 amp
- 2.1.2 Single phase, three wire, 240/480 volt, up to 400 amp

2.2 Stores Item Number - **236734**

**3. TYPE TR-8 (8 jaws)**




3.1 Application

- 3.1.1 Three phase, three wire, 240 volt, over 200 amp
- 3.1.2 Three phase, three wire, 480 volt, any size

3.2 Stores Item Number - **236735**

**4. TYPE TR-13 (13 jaws)**



4.1 Application

- 4.1.1 Three phase, four wire, 120/208 volt, over 200 amp
- 4.1.2 Three phase, four wire, 277/480 volt, any size
- 4.1.3 Three phase, four wire, primary voltage service

4.2 Stores Item Number - **236736**